

LED-754 LED Industrial High-Light Searchlight



FEATURES:

- .Rated Capacity : more than 14000mAh
- .The product uses switch power charger, relay switch and double-color charging indicator light
- .Long life battery could be cycling used more than 500 times
- .Use LED bulbs are of energy saving, high efficiency, and long using life

PARAMETER:

- Product Material: ABS environmentally friendly raw materials
- Product Color: 、 Blue
- Number of LED: 4
- Power Supply Mode: Built-in high capacity battery
- Battery Capacity: 14000mAh
- Usable Time: 10 hours
- Dimension: 175x185x243mm
- Weight: 2270 gr

TECHNOLOGY:

- Light Source Power: 12W
- Rated Voltage: AC90-240V~ 50/60Hz
- Rated Current: DC1.2A

INSTRUCTIONS:

- During charging, please connect the cable with holes into AC outlet of the searchlight, then insert the AC plug of the cable into the power (AC90-240V~). The charging indicator will now turn red to show the charging process. It will turn green when it is full. At this moment you should take out the cable to protect the battery
- To press the switch is to control the searchlight on or off. When the voltage of the battery is lower than the working voltage of the relay, the relay will not work and the indicator light is off. When the battery voltage is higher than the relay voltage, the relay will start working, and the indicator is on
- .To press the switch, 4 LED will turn on; To press it again, 4 LED will be off
- .After fully charged, it could be used for about 10 hours when pressing the switch
- When the led bulb is dim during usage, that means the battery is at the stage of discharging. Please stop using and charge it in time to protect the battery. (Please charge before the led bulb is dark fully, otherwise the (battery would be damaged
- Searchlight should be usually used, please don't lay it aside for a long time. Please charge it over 10 hours every 3 months if you don't usually use it, or it would reduce the lifetime of the battery

PRECAUTIONS:

- .The power and socket must be safe and standard
- .Please don't use when charging, it would burn LED bulbs, or damage inner components
- (Please don't shot the eyes directly, it would effect the eyesight. (Children must be instructed by adults
- .Keep away from rain or wet
- Keep far away from the exploders when charging, the charging time could not be more than 24 hours
- After fully charged, it could be used for about 10 hours when pressing the switch